

# GOODWE

## A-ES Series

(Americas Only) 5-9.6kW | Split Phase Hybrid Inverter | HV Battery | Up to 4 MPPTs  
UL certified

The GoodWe A-ES Series is a split-phase hybrid inverter designed to increase self-consumption of your generated solar energy. GoodWe A-ES is compatible with high voltage (80-495V) batteries with a power capacity ranging from 5kW to 9.6kW. With up to 4 MPPTs, the A-ES inverter seamlessly adapts to complex residential rooftops. Equipped with rapid battery charge functionality and perfectly capable of powering large loads in back-up mode (up to 9.6kW).



Seamless UPS Switch Function



AFCI & Rapid Shutdown



4 MPPTs & 150% DC Input Oversizing



Smart Meter Integrated

Technical Data	GW5000A-ES	GW6000A-ES	GW7000A-ES	GW7600A-ES	GW8600A-ES	GW9600A-ES
<b>Battery Input Data</b>						
Battery Type	Li-Ion					
Battery Voltage Range (V) <sup>1</sup>	80 ~ 495					
Max. Continuous Charging Current (A)	50					
Max. Continuous Discharging Current (A)	50					
<b>PV String Input Data</b>						
Max. Input Power (W)	7500	9000	10500	11400	12900	15000
Max. Input Voltage (V) <sup>2</sup>	600					
MPPT Operating Voltage Range (V) <sup>3</sup>	80 ~ 550					
Start-up Voltage (V)	95					
Nominal Input Voltage (V)	380					
Max. Input Current per MPPT (A)	12.5 / 12.5	12.5 / 12.5	12.5 / 12.5 / 12.5 / 12.5	12.5 / 12.5 / 12.5 / 12.5	12.5 / 12.5 / 12.5 / 12.5	12.5 / 12.5 / 12.5 / 12.5
Max. Short Circuit Current per MPPT (A)	15.2 / 15.2	15.2 / 15.2	15.2 / 15.2 / 15.2 / 15.2	15.2 / 15.2 / 15.2 / 15.2	15.2 / 15.2 / 15.2 / 15.2	15.2 / 15.2 / 15.2 / 15.2
Number of MPPTs	2	2	4	4	4	4
Number of Strings per MPPT	1 / 1	1 / 1	1 / 1 / 1 / 1	1 / 1 / 1 / 1	1 / 1 / 1 / 1	1 / 1 / 1 / 1
<b>AC Output Data (On-grid)</b>						
Max. Apparent Power Output to Utility Grid (VA)	5000	6000	7000	7600	8600	9600
Max. Apparent Power from Utility Grid (VA)	6000	7200	8400	9120	9600	9600
Output Voltage Range (Vac)	211 to 264 @240					
Nominal AC Grid Frequency (Hz)	60					
Max. AC Current Output to Utility Grid (A)	20.8	25.0	29.2	31.7	35.8	40.0
Max. AC Current From Utility Grid (A)	25	30	35	38	40	40
Power Factor	~1 (Adjustable from 0.8 leading to 0.8 lagging)					
Max. Total Harmonic Distortion	<3%					
<b>AC Output Data (Back-up)</b>						
Max. Output Apparent Power@240V (VA)	5000 (6000@60sec)	6000 (7200@60sec)	7000 (8400@60sec)	7600 (9120@60sec)	8600 (10320@60sec)	9600 (11520@60sec)
Max. Output Current@240V (A)	20.8	25.0	29.2	31.7	35.8	40.0
Nominal Output Voltage L1-L2 / L-N (Vac)	240 / 120					
Nominal Output Frequency (Hz)	60					
Output THDv (@Linear Load)	<3%					
<b>Efficiency</b>						
Max. Efficiency	97.6%					
CEC Efficiency	97.3%	97.4%	97.1%	97.1%	97.1%	97.1%
Max. Battery to AC Efficiency	96.6%					
<b>Protection</b>						
PV Insulation Resistance Detection	Integrated					
Residual Current Monitoring	Integrated					
PV Reverse Polarity Protection	Integrated					
Battery Reverse Polarity Protection	Integrated					
Anti-islanding Protection	Integrated					
AC Overcurrent Protection	Integrated					
AC Short Circuit Protection	Integrated					
AC Overvoltage Protection	Integrated					
PV Arc Fault Detection	Integrated					
<b>General Data</b>						
Operating Temperature Range (°F)	-31°F ~ 140°F (-35°C ~ 60°C)					
Relative Humidity	0 ~ 95%					
Max. Operating Altitude (ft)	≤13123ft (4000m)					
Cooling Method	Intelligent Fan					
Display	LED & APP (WiFi, Bluetooth)					
Communication with BMS	RS485; CAN					
Communication with Meter	RS485					
Communication with Portal	Wi-Fi; LAN (Optional)					
Weight (lb)	62.8lb (28.5kg)	62.8lb (28.5kg)	70.5lb (32kg)	70.5lb (32kg)	70.5lb (32kg)	70.5lb (32kg)
Dimension W x H x D (inch)	16.3 x 31.1 x 6.9 in (415 x 790 x 175 mm)					
Noise Emission (dB)	<45					
Topology	Transformerless					
Self-consumption at Night (W) <sup>4</sup>	<20					
Ingress Protection Rating	NEMA Type 4X					
Mounting Method	Wall Bracket					
<b>Certification</b>						
Grid Standards	UL1741 SA, California Rule 21, HECO Rule 14, IEEE 1547, IEEE 1547.1					
Safety Regulation	UL 1741, CSA 22.2 No. 107-01, UL 1998, UL1699B					
EMC	FCC part15 CLASS B					

\*1: Battery discharge / charge power limited by voltage.  
 \*2: Inverter will not work when PV input voltage ≥585V.  
 \*3: When there is no battery connected, inverter starts feeding in only if string voltage is higher than 200V.  
 \*4: No Back-up Output.  
 \*: Peak output apparent power@240V can be reached only if battery power is enough.  
 \*: Please visit GoodWe website for the latest certificates.